

Adding & Managing Command Centers & Scouts

Standard procedures to add, delete, and upgrade Lumeta components (aka systems) follow.

Add System ▾

Delete System

Upgrade Connected Scouts

1. [Log on](#) to Lumeta.
2. Navigate to **Settings > Lumeta Systems**.
3. Add, delete, or upgrade components, as needed:
 - a. To add a Lumeta Command Center:
 - i. Click **Add System**.
 - ii. Enter the system name or IP address.
 - iii. Click **Add System**.
 - b. To delete a Lumeta Command Center:
 - i. On the **Settings > Lumeta Systems** page, click **Delete System**.
 - c. To upgrade all Scouts connected to your Command Center:
 - i. Check the [Release Notes](#) to your intended upgrade so you'll be apprised of special information concerning the Scout along with a summary of new features, enhancements, fixes, and security updates.
 - ii. Log in to your [FireMon User Center](#) account to access the upgrade. If you need credentials, contact lumetasupport@firemon.com.
 - iii. Navigate to the Downloads page.
 - iv. In the Lumeta panel, click the upgrade package you need and download it to your local system.
 - v. [Log in](#) to a Lumeta Command Center.
 - vi. Browse to **Settings > Lumeta Systems**.
 - vii. In the Available Systems column, select a Command Center.
 - viii. Click **Upgrade Connected Scouts** to upgrade all Scouts connected to it.
 1. Browse to and select the **upgrade tgz** file you downloaded to your local system.
 2. Select the Scouts to upgrade.
 - ix. Click **Submit**.

The upgrade is in progress.
 - x. Validate that the installation completed successfully by browsing to the IP address of your Scouts.

The Scout's new version number should display as intended.