

# BlueCat Configuration

A Asset Manager admin or superuser can configure connectivity between the Asset Manager Command Center and the BlueCat server to compare and share IP address management findings.

Here's how:

- 1. [Log in](#) to Asset Manager as an admin or any user with superuser privileges.
- 2. On the main menu, browse to **Settings > Integrations > BlueCat**.
- 3. Complete the configuration form and click **Submit**.



☒ On

Polling Interval (by Hour)

24

Server Name

172.16.52.60

Username

gateway

Password

Leave blank to use the previously-entered p

- ☒ Add unmanaged devices with no network block defined

Retrieve Configurations

Lumeta Zones	BlueCat Configuration Name	Enabled
Zone1	<div>Boston</div>	<input checked="" type="checkbox"/>
zone2	<div>Boston</div>	<input checked="" type="checkbox"/>

Submit

✔ Product configured properly.

Field	Description
Polling Interval	How often (in hours) Asset Manager should poll the BlueCat gateway
Server Name	The server name or IP address of the BlueCat gateway
Username	User account to the BlueCat gateway

Password	Password to the BlueCat gateway
Retrieve Configurations	Fetches network configurations from the gateway
Add unmanaged devices with no network block defined	<ul style="list-style-type: none"> <li>• Select to create a new device in BlueCat Address Manager (BAM) <i>even when there is not a container network address block for the device.</i></li> <li>• Clear to NOT create a device in BlueCat Address Manager (BAM) <i>when a container block does not exist for the device.</i></li> </ul>
Option	Behavior
No zones are enabled	No assets will be pushed to BAM
One zone is enabled however, no configuration is selected under BlueCat Configuration Name	User has to select a configuration in order to push assets to BAM. No assets will be pushed to BAM
One zone and one configuration is selected	Asset Manager would identify all ip addresses discovered under selected zone and add ip addresses under selected configuration
Two zones and two configurations are selected	Asset Manager would identify all ip addresses discovered under selected zones and add ip addresses under selected configuration for the ip address that don't exist in selected configuration for that zone

4. Enable the integration by toggling the Active control from red to blue.  
The message "Product configured properly" will display.

Install the [BlueCat Plugin](#) if you have not done so already.

Review the results on the [BlueCat Management](#) dashboard.